

AC -> DC SWITCHING POWER SUPPLY

## Features

Patents Held

# **Green Power**

- C C C C
- Standard/Din Rail Mounting Dual Purpose
- No-load Consumption is lower than 0.3W (No Display)
- Comply with High Efficiency Power 80Plus Criterion
- Comply with 2010. Energy Conservation Power Erp Regulation
- " Output Voltage Monitor " Display
- Convection cooled high reliability
- Wide input range
  - 100% burn-in test
- 1 years warranty
  - Output modify range: 3V~200VDC

DIMENSIONS: 102(H) \* 75.5(D) \* 45(W)mm

WEIGHT: 181g

## **General specification**

## <u>INPUT</u>

Input range

Input frequency Inrush current (25°C)

#### 90~264VAC 127~380VDC 47~63Hz 20A/110VAC 40A/220VAC

## <u>OUTPUT</u>

Hold-up time Short protection Over load protection 13ms Autorecovery Automatic power limited

## **Detail specification**

40~50 Watts 12Vdc & 24Vdc Model stocked in UK - 5Vdc model available on request

MODEL	O/P Volt	Load(Current) 1			Ripple Line	Line	Load	Efficiency	O.V.P
MODEL	Adj. ± %	<sup>%</sup> Min. Rated Max. Noise 4 REG	REG.	REG.	5	0.v.P			
LP1040D-05S	V : +5V ±10%	0A	8.0A	8.0A	50mV	±1%	±1%	81% Ref.	7.13 ~ 7.88V
LP1050D-12S	V : +12V ±10%	<mark>0A</mark>	<mark>4.2A</mark>	<mark>4.2A</mark>	<mark>120mV</mark>	<mark>±1%</mark>	<mark>±1%</mark>	<mark>85% Ref.</mark>	<mark>17.1 ~ 18.9V</mark>
LP1050D-24S	<mark>V : +24V ±10%</mark>	<mark>0A</mark>	<mark>2.1A</mark>	<mark>2.1A</mark>	<mark>240mV</mark>	<mark>±1%</mark>	<mark>±1%</mark>	<mark>86% Ref.</mark>	<mark>31.4 ~ 34.7V</mark>

#### Please choose functions and fill in The blanks

Order Model:LP1050D-12S Optional Function: Terminal Block: " " : PCB Barrier Te "E" : Mini Terminal B		Aonitor Type: " " : No Display Function itor Display - "A" : Output Voltage Displa	
EMC Standards	Safety Standards	Environment	
EN 55022 CLASS A EN 61000-3-3, EN 55024 (IEC 61000-4-2, IEC 61000-4-3,IEC 61000-4-4, IEC 61000-4-5IEC 61000-4-6, IEC 61000-4-8IEC 61000-4-11)	UL 508 APPROVAL	Operating Humidity5 ~ 95% RH, NoStorage Temperature-20 ~ 8	0°C, Ambient Condensing 5°C, Ambient 00Hz, 3 axes

## <u>NOTE</u>

- **1.** Each output can provide up to maximum load, but total load cannot exceed rated output power.
- 2. Line regulation is measured from low line to high line at rated load.
- 3. Load regulation is measured from 20% to 100% of rated load at 220VAC input.
- 4. Ripple & noise are measured at 20MHz of bandwidth by using a 20cm long 12" twisted pair-wire terminated with a 0.1uF & 47uF parallel capacitor.
- 5. Efficiency is measured at rated load and 220VAC input.
- 6. Hold-up time is measured at rated load and 220VAC input.
- 7. Output voltage monitor display models. no-load power consumption of 1.5W. and no Energy Conservation Power Erp Regulation.
- 8. Reign Power reserve the right to change specifications at any time without notice.

WEB : http://www.switching-powers.com E-mail : reignpower@switching-powers.com Tel: 886-2-22997550 Fax: 886-2-22997596

